

[illegible]

BACKGROUND

1

[0021] Figure 16 illustrates a cross section of the outside rotation yoke shown in Figure 15.

[0022] Reference will now be made in detail to the present embodiment of the invention, an example of which is illustrated in the accompanying drawings.

DESCRIPTION OF THE PREFERRED EMBODIMENT

[0023] Figure 1 illustrates a cross section view of motor 10 that is capable of both rotary and linear motion. This motor has a rotor assembly 20 and a casing 40.

[0024] Rotor assembly 20 may be formed from shaft 22, key 24, translate magnet 26, magnet spindle 32, and rotation magnet 34. Figures 2 and 3 provides detailed views of key 24. Figure 4 shows the magnetic polarity for an exemplary translate magnet 26. Figure 5 and 6 provide additional details for an exemplary segmented magnet that may be utilized as a rotation magnet 34. Key 24, translate magnet 26, and rotary magnet 34 are operably connected to shaft 22. Rotation magnet 34 may be operably connected to shaft 22 with magnet spindle 32. Typically, key 24 and rotation magnet 34 are operably connected to shaft 22 in such a manner that these pieces will not rotate with respect to shaft 22. Translate magnet 26, however, does not require to be operably connected to shaft 22 in such a manner that rotation of translate magnet 26 with respect to shaft 22 is prevented. Translate magnet 26 may be positioned between key 24 and magnet spindle 32 such that translate magnet 26 is limited or prevented from moving along shaft 22. Since translate magnet 26 is used to move the rotation assembly 20 and key 24

axially to remove key 24 from key indent 43 in key way bushing 44, the only requirement is that translate magnet 26 remain relatively stationary with respect to the axis of shaft 22 when the translate coil 60 is energized and results in linear motion of rotor assembly 20. One method of operably connecting shaft 22 to key 24 and magnetic spindle 32 is by using an interference fit between these parts whereby during assembly the key 24 and magnet spindle 32 are pressed onto shaft 22.

[0025] Casing 40 is designed to permit both rotary and linear motion of rotor assembly 20. This casing has a first end plate 42, shown in detail in Figures 7 and 8, and a second end plate 46. Inset into each end plate is a bushing. Key way bushing 44 is inserted into a bushing opening in the first end plate 42. The second end bushing 48 is inserted into the second end plate 46. These bushings are selected from materials that typically have low friction coefficients to reduce the amount of power consumed in either the rotation or translation phases of rotor assembly 20.

[0026] Between the end plates 42 and 46 are the coils and their supporting yokes that are utilized to create the magnetic fields that cause rotor assembly 20 to move both axially and rotationally. Translation is caused by a combination of the translate coil 60 contained within the outer translation yoke 50 and inner translate yoke 52. Details of yokes 50, 52 are provided in Figures 9-12. The coil 60 shown is wound like a bobbin and as a result creates a magnetic field with a different pole at each end of coil 60.

[0027] Outer translate yoke 50 has translate fingers 51 that are utilized to direct the magnetic field oriented towards first end plate 42 up and along the sides of translate magnet 26. The use of translate fingers 51 while

optional serve to increase the magnetic field experienced by the translate magnet 26. Consequently, a smaller magnetic field is required to be generated by translate coil 60 to cause translate magnet 26 to move rotor assembly 20 the required distance so that key 24 clears key way bushing 44 or keyed gear clears the external detent; permitting motor 10 to rotate.

[0028] Inner yoke 52 shown does not have any fingers so that there will not be any competing magnetic field to interfere with the action of the translate magnet 26.

[0029] The translate coil 60 lies for the most part between the inner and outer translate yokes 52, 50. Thus, in some embodiments, the inner and outer yoke may provide some structural support to translate coil 60. Since the outer translate yoke 50 may be utilized to direct the magnetic field created by translate coil 60 it is desired but not required that this material be magnetically permeable. Examples of such materials are iron and steel and other ferrous materials.

[0030] In the current embodiment the translate coil 60 generates a magnetic field in outer translate yoke 50 that is the same polarity as found at magnet face 28. Consequently, translate magnet 26 is repelled from outer translate yoke 50. Alternatively, the inner translate yoke 52 could be formed with fingers and the outer translate yoke 50 without fingers. In this case the magnetic field generated in inner translate yoke 52 by coil 60 could either attract translate magnet 26 or repel translate magnet 26 depending on the direction of motion utilized to remove key 24 from detent 43 of bushing 44 or keyed gear from the external detent.

description of the preferred embodiment of the invention has been presented for the purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to a precise form disclosed. Obvious modifications or variations are possible in light of the above teachings. The embodiment was chosen to describe in order to best illustrate the principles of the invention and its practical application to thereby enable one of ordinary skill in the art to best utilize the invention in various embodiments and with various modifications as there suited particular use contemplated. It is intended that the scope of the invention be defined by the claims appended hereto.

TOCTHO: SE6E660